

Amendments to the Claims:

The following listing of claims will replace all prior versions, and listings, of claims in the application:

Proposed claims:

1. (Currently Amended) An electronic circuit that changes a reference voltage value with a transforming circuit using a threshold voltage of a transistor to supply the reference voltage to control terminals of a plurality of current-generating active elements, establishes a conduction state of the plurality of the current-generating active elements, and selects some of the plurality of current-generating active elements based on signals and generates a current having a current level corresponding to the signals by superposing currents passing through the current-generating active elements selected by the signal, from among the plurality of current-generating active elements.

2. (Currently Amended) An electronic circuit, comprising:
a plurality of current-generating active elements;
a transforming circuit that generates an applied voltage that is applied to control terminals of the plurality of current-generating active elements by using a threshold voltage of a transistor to change ~~changing~~ a reference voltage; and
selection transistors connected in series to each of the plurality of the current-generating active elements,
a current having a current level corresponding to signals being generated by superposing the currents that pass through a selection transistor in which an ON-state is selected, among the selection transistors, based on the signal-signals and the current-generating active elements connected in series to the selected selection transistor from among the plurality of current-generating active elements.

3. (Currently Amended) The electronic circuit according to Claim 1, the transforming circuit comprising a compensating transistor ~~having~~ that reduces the reference voltage value by a predetermined value or that adds a predetermined value to the reference voltage value.

4. (Previously Presented) The electronic circuit according to Claim 1, each of the plurality of current-generating active elements including at least one transistor.

5. (Previously Presented) The electronic circuit according to Claim 1, the plurality of current-generating active elements being connected in parallel to each other.

6. (Currently Amended) The electronic circuit according to Claim ~~4~~3, each of the plurality of current-generating active elements comprising one current generating transistor and the current generating transistors having different gain factors from each other.

7. (Currently Amended) The electronic circuit according to Claim ~~4~~3, at least one current-generating active element from among the plurality of the current-generating active elements being connected in series to a unit transistor.

8. (Currently Amended) The electronic circuit according to Claim 7, the compensating transistor being a transistor having a characteristic ~~almost~~ equal to that of the unit transistor.

9. (Currently Amended) The electronic circuit according to Claim 6, the current generating transistors and the compensating ~~transistors~~ transistor being formed at positions adjacent to each other and have ~~almost~~ the same threshold voltage value.

10. (Currently Amended) The electronic circuit according to Claim ~~4~~3, the transforming circuit comprising an initializing device that turns on the compensating transistor.

11. (Previously Presented) The electronic circuit according to Claim 1, the transforming circuit comprising a voltage-stabilizing device.

12. (Previously Presented) The electronic circuit according to Claim 11, the voltage-stabilizing device comprising capacitors.

13. (Currently Amended) An electro-optical device, comprising:
a control circuit that outputs digital luminance gradation data;
a driving circuit that generates an analog driving signal based on the digital luminance gradation data; and
a pixel circuit that drives an electro-optical element based on the analog driving signal,
the driving circuit using a threshold voltage of a transistor to change ~~changing~~ a reference voltage value with a converting circuit to supply the reference voltage to control terminals of a plurality of current-generating active elements and to establish a conduction state in the plurality of current-generating active elements, and selecting some of the plurality of current-generating active elements based on the digital luminance gradation data, and superposing currents that pass through an current-generating active elements selected by the digital luminance gradation data, from among the plurality of current-generating active elements, to thereby generate an analog driving signal having a current level corresponding to the digital luminance gradation data.

14. (Currently Amended) An electro-optical device, comprising:
a control circuit that outputs digital luminance gradation data;
a driving circuit that generates an analog driving signal based on the digital luminance gradation data; and
a pixel circuit that drives a current driving element based on the analog driving signal,
the driving circuit comprising a plurality of current-generating active elements;
a transforming circuit that generates an applied voltage which is applied to control terminals

of the plurality of current-generating active elements by using a threshold voltage of a transistor to change ~~changing~~ a reference voltage; and selection transistors connected in series to each of the plurality of current-generating active elements, and

a current having a current level corresponding to said digital luminance gradation data being generated by superposing the currents that pass through a selection transistor in which an ON-state is selected, from among the selection transistors, based on the signal and the current-generating active elements connected in series to the selected selection transistor from among the plurality of current-generating active elements.

15. (Previously Presented) The electro-optical device according to Claim 13, the transforming circuit comprising a compensating transistor that reduces the reference voltage value by a predetermined value or that adds a predetermined value to the reference voltage value.

16. (Previously Presented) The electro-optical device according to Claim 13, each of the plurality of current-generating active elements comprising at least one transistor.

17. (Previously Presented) The electro-optical device according to Claim 13, the plurality of current-generating active elements being connected in parallel to each other.

18. (Currently Amended) The electro-optical device according to Claim ~~13~~15, each of the plurality of the current-generating active elements comprising a current generating transistor, and the current generating transistors having different gain factors from each other.

19. (Currently Amended) The electro-optical device according to Claim ~~13~~15, at least one of the plurality of current-generating active elements being connected in series to a unit transistor.

20. (Currently Amended) The electro-optical device according to Claim 19, the compensating transistor being a transistor having a characteristic ~~almost~~ equal to that of the unit transistor.

21. (Currently Amended) The electro-optical device according to Claim 18, the current generating transistors and the compensating ~~transistors~~ transistor being formed at positions adjacent to each other, and have ~~almost~~ the same threshold value voltage.

22. (Currently Amended) The electro-optical device according to Claim ~~13~~ 15, the transforming circuit comprising an initializing device that turns on the compensating transistor.

23. (Previously Presented) The electro-optical device according to Claim 13, the transforming circuit comprising a voltage-stabilizing device.

24. (Previously Presented) The electro-optical device according to Claim 23, the voltage-stabilizing device comprising capacitors.

25. (Previously Presented) The electro-optical device according to Claim 13, the electro-optical element being an electroluminescent (EL) element.

26. (Previously Presented) The electro-optical device according to Claim 25, the EL element comprising a light-emitting layer made up of organic materials.

27. (Previously Presented) An electronic apparatus packaged with the electronic circuit according to Claim 1.

28. (Previously Presented) An electronic apparatus packaged with the electro-optical device according to Claim 13.

29. (Currently Amended) The electronic circuit as set forth in Claim ~~17~~ 7, at least one current generating active element of the plurality of current generating active elements ~~including~~ having a parallel connection ~~of~~ to the unit transistor.

30. (Currently Amended) The electro-optical device as set forth in claim ~~13~~ 19, at least one current generating active element of the plurality of current generating active elements ~~including~~ having a parallel connection ~~to~~ of the unit transistor.